

Bols

ceiling light



Table of contents

1. Product overview	Page 2
2. Finishes and materials	Page 2
3. Light Source & dimming	Page 2
4. Ordering codes	Page 3
5. Certifications & standards	Page 4
6. Maintenance & Cleaning	Page 4

Versions



4023X
Page 3

Bols

ceiling light

1. Product overview

Outdoor aluminium ceiling light with polyethylene shade and integrated dimmable LED. Double layer coating for high resistance.



2. Finishes and Materials



Shade: Polyethylene

Body: 55 Beige

3. Light Source & Dimming

Lamping

LED 10W (2700K / Ang. 120° / >90 CRI)

230V / Typ* 870 lumens

*Integrated LED module (included).

Dimming options:

Standard: TRIAC

Optional: DALI, CASAMBI

Bols

ceiling light

4. Ordering Codes

Lamping
LED 10W (2700K / Ang. 120° / >90 CRI)
230V / Typ* 870 lumens
*Integrated LED module (included).

Finishes
55 Beige



DIM: TRIAC (Optional DALI, CASAMBI)

Drawing	Mounting	Setting	Finish Body	Ordering Code
BOL_4023X IP 65 Front view dimensions: $\varnothing 205\text{ mm}$ / $\varnothing 8.1/8''$, 285 mm / $11.1/4''$, 40 mm / $1.5/8''$, $\varnothing 800\text{ mm}$ / $\varnothing 31.1/2''$. Top view dimensions: 360 mm / $15''$, $\varnothing 350\text{ mm}$ / $\varnothing 13.3/4''$, $\varnothing 800\text{ mm}$ / $\varnothing 31.1/2''$.	Ceiling light. Surface mounted.	Outdoor	Beige	BOL_4023X_55W

Bols

ceiling light

5. Certifications & Standards



Warranty: 2 years

100% made in Spain

6. Maintenance & Cleaning

Our lighting fixtures are crafted with high-quality materials and finishes to ensure durability and timeless elegance. To maintain their original beauty, please follow these care recommendations:

1. Regular cleaning: Dust the fixture regularly using a soft, dry microfiber cloth to prevent buildup.
2. For deeper cleaning: If necessary, use a slightly damp cloth with clean water. Always dry the surface immediately with a dry cloth.
3. Avoid harsh products: Do not use alcohol, abrasive cleaners, solvents, or detergents, as they may damage the finish and alter the appearance.

In case of failure, LEDs can be easily replaced.