


# TUBE CARRÉ wall 1.0 PAR16

INSTALLATION INSTRUCTIONS | APRIL 2025

## DIMENSIONS



1.0 PAR16


## MOUNTING INSTRUCTION

- 1 Remove the backplate by loosening the socket screws and fix it to the wall with screws (screws are not included).


## 2 POWER CONNECTION

Connect to 220-240V.

Connect the earth cable.



Always use a matching grommet based on the used 220-240V cable and the corresponding type in the overview table.




Push the grommet into the back plate.

Pull the cable through the back plate.

Mount the back plate on the wall.

- 3 a. Open the cover with a flat screwdriver.  
b. Loosen the four screws of the glass cover and remove it.  
c. Insert the lamp.  
d. Put back the glass cover with the four screws.  
e. Place back the body cover by pushing.
- 4 Mount the luminaire on the backplate with the socket screws.

backplate:



Always use a matching grommet in the overview table.

|                    |                                                                                   |                                                    |                                           |
|--------------------|-----------------------------------------------------------------------------------|----------------------------------------------------|-------------------------------------------|
|                    | A                                                                                 | B                                                  | C                                         |
|                    |                                                                                   |                                                    |                                           |
| CABLE              |                                                                                   |                                                    |                                           |
| TYPE               | ROUND<br>H05RN-F<br>H07RN8-F<br>H07RN-F                                           | ROUND<br>H05RN-F                                   | ROUND                                     |
| OUTSIDE Ø          | min 6.8mm<br>max 8.9mm                                                            | min 5mm<br>max 6.8mm                               | min 1.5mm<br>max 2.6mm                    |
| CONDUCTION SECTION | 2or3x 0.75mm <sup>2</sup><br>2or3x 1.0mm <sup>2</sup><br>2or3x 1.5mm <sup>2</sup> | 2or3x 0.75mm <sup>2</sup><br>2x 1.0mm <sup>2</sup> | 0.75mm <sup>2</sup><br>1.5mm <sup>2</sup> |



WEVER & DUCRÉ  
LIGHTING

WEVER & DUCRÉ BV

Spinnerijstraat 99/21, 8500 Kortrijk, Belgium  
weverducre.com

PB19-010-548-00\_v4